

SANGEAN

SINCE 1974

PR-D4



FM–Stereo / AM / PLL Receiver

- PLL Synthesized tuning system.
- 10 memory presets (FM5, AM5).
- Rotary volume control.
- LCD displays separately clock and radio information.
- Auto station scan.
- Two alarm timers (radio and buzzer).
- Snooze.
- Sleep (auto shut off).
- Battery power status indication.
- 3 inch full range speaker.
- Long lasting battery operation.
- DC 6 V jack.
- Headphones jack.

E&OE

See over page for technical specifications.

CANOHM

4/30 Prohasky Street,
Port Melbourne Victoria 3207

Telephone 03 9644 7888
Facsimile 03 9646 7366

Email
orders@canohm.com.au

www.sangean.com.au
www.canohm.com.au

ABN 57 004 817 949
November 2016

PR-D4

Specifications

Tuning	Type	PLL synthesizer
	Memory Presets	10
Display	Type	LCD
	Size (mm)	99.6 x 24.6
	Back light	Yes
Band	FM	Frequency MHz 87.5 - 108
		Stereo via headphones
	AM	Frequency kHz 522 - 1629
Clock	Real time	Yes
	Alarm Radio	Yes
	Alarm Buzzer	HWS
	Snooze	Yes
	Sleep	Yes
Output	Speaker unit	3 inch 4 ohm
Output Power	AC/DC IN (Speaker)	
	Batteries (Speaker)	700 mW
	Earphones	5 + 5 mW
Power Supply	DC IN	6 V DC 400 mA
	Batteries (Main Power)	4 x 1.5 V (UM-I)
I/O Socket	DC In	Yes
	Earphones	Yes
Accessories	AC Adapter	Yes (with Pr-D4AD version)
Dimensions	W x H x D (mm)	237 x 148 x 62
	Weight (g)	840
Warranty		12 months

