



DT-120

FM-Stereo / AM Pocket Receiver



AUTO SCAN



STEREO BY EARPHONE



LOCK

● WHITE ● BLACK

Features

- Direct recall 15 station presets (5 FM1 / 5 FM2 and 5 AM)
- Built-In real time clock
- RF signal level indicator
- Adjustable tuning step
- DBB (Dynamic Bass Boost)
- Stereo/Mono switch
- 90-Minute auto Shut-Off
- Lock switch
- Battery power indicator
- Hand-held size

Specifications

TUNER	FM	Frequency (MHz)	87.5 - 108
	AM/MW	Frequency (kHz)	522 - 1710 (9k) / 520 - 1710 (10k)
	Memory Presets		15 (5 AM / 5 FM1 / 5 FM2)
CLOCK	Real Time		●
	Sleep		Auto Shut-Off (90min)
DISPLAY	LCD / VFD / Dial Scale		LCD
	View Area (mm / inch)		29.6 x 15 / 1.17 x 0.59
	Graphic / Character Type		Segment
FEATURE	Stereo		Earphones
AUDIO	Sound Effect	DBB	●
OUTPUT POWER	Earphones Output Power		2.5mW x 2
I/O SOCKET	Earphones		●
POWER SUPPLY	Batteries (Main Power)		2 x 1.5V (AAA)
ACCESSORIES	Earphones		●
DIMENSIONS	Width (mm/inch)		49 / 1.93
	Height (mm/inch)		92.5 / 3.64
	Depth (mm/inch)		16.2 / 0.64
	Weight (g & lb.)		56 / 0.12

4/30 Prohasky Street, Port Melbourne, Vic, 3207

T 1800 636 026 E orders@canohm.com.au

CANOHM.COM.AU