

FM / AM / Bluetooth Wooden Cabinet Receiver

- FM / AM 2 bands
- Built-in Bluetooth wireless audio streaming
- Easy to pair your NFC (Near Field Communication) enabled smartphone via Bluetooth with a simple tap
- Tuning and band indicators
- Soft and precise tuning

- Deep bass compensation for rich bass
- 3-inch 10 watt full range speaker with enlarged magnet
- Auxiliary input for additional audio sources
- Line-out jack socket connection for audio amplified speaker system





See over page for technical specifications.



SPECIFICATIONS

Tuner	FM	Frequency (MHz)	87.5 - 108
	AM	Frequency (kHz)	520 - 1710
	Bluetooth		Yes
Media			Bluetooth wireless audio
Bluetooth		NFC	Yes
Feature		Bluetooth	V2.1 class-II
Amplifier		Speaker Output (Typ.)	6.5 W (AC)
		Earphones Output	5 + 5 mW (32 ohm)
Speaker		Size	3 inches
		Impedance	8 ohms
		Magnetically Shielded	Yes
I/O Socket		AC / DC - in	DC
		Aux - in	Yes
		Line - out	Yes
		Earphones	Yes
		Ext. Antenna	FM
Power Supply		DC in	Yes
Accessories		AC Adapter	12V / 1.2 A
Dimensions		$W \times H \times D \text{ (mm)}$	120 × 204 × 152
		Weight (g)	1650
Particular Perfori	mance		Deep Bass Compensation
Warranty			12 months

WR-I5BT











